FUMECUBE MAX



The Future of Fume Extraction **Henchman Products** Official Australian Agent



FEATURES

- VariColour filter blocked warning system
- Highest grade HEPA and carbon technology
- Automatic electronic flow control maintains a constant extraction rate even as the filter blocks
- Quiet in operation
- · Simple to install and easy to relocate

SPECIFICATIONS

Voltage	230v	90v - 254v
Wattage	0.14kW	0.21kW
Frequency	50Hz / 60Hz	50Hz / 60Hz
Cabinet Height	493mm	493mm
Cabinet Width	308mm	308mm
Cabinet Depth	330mm	330mm
Cabinet Weight	14kg	14kg
Sound Level	<60dBa	<60dBa
Airflow	170m3/h	160 - 200m3/h

INCLUDED AS STANDARD...

FILTERS



Main Filter Code 110507

Description HEPA/Chemical



Pre-filter Code 111124

Description F8/F9 Labyrinth

Find out more:



www.purex.co.uk



purex@purex.co.uk



+44 (0)1405 746030

CONNECTION KIT

Connection kit is included see overleaf for options


Main Filter

Code: Description: 110504 Chemical

Connection Kits

Machine + Hose Kit

Voltage	Part Number
230v	072140
Multi Voltage	072141




Includes:

3m x 50mm flexible hose 2 x connecting cuffs



Machine + 38mm Single Arm Kit

Voltage	Part Number
230v	072142
Multi Voltage	072143




38mm Single arm kit includes:

- 1 x 80 51mm reducer
- 1 x Arm Kit (100295) see below

Machine + 38mm Dual Arm Kit

Voltage	Part Number
230v	072144
Multi Voltage	072145



38mm Dual arm kit includes:

1 x 80 - 51mm dual manifold 2 x Arm Kits (100295) see below

100295

Includes:

- 1 x 2m x 50mm flexible hose
- 2 x connecting cuffs
- 1 x 38mm stainless steel flexible arm with valve
- 1 x 95mm conical cowl
- 1 x 38mm pen nib
- 1 x clamped bench bracket



Replacement Arms

Code:

120199

120128 38mm x 1.5m flexible stainless steel arm

120129 38mm x 0.75m flexible stainless steel arm

> 38mm x 0.5m flexible stainless steel arm

Description:



Interfacing

Your Machine 10011010 Extractor

Interfacing can remotely start the Purex machine when the connected machine starts.

Interfacing can also warn the connected machine when the Purex machine is in alarm.

Take a look through our Interfacing Guide to see our extensive range of options



Purex International Limited QWP House, Island Drive Capitol Park, Thorne Doncaster, UK DN8 5UE

www.henchman.com.au